



Kentronics
1467 Bribie Island Road
Ningi, Qld, 4511

ABN: 14 857 805 435

Ph: 07 5429 5363

Fax: 07 5429 5364

Mobile: 0417 377 480

Email: kenton@kentronics.com.au

POSTEC FCC3 Master Reset

Remove cover from FCC3 & document switch settings on "S1" 4 bank DIP Switch.

Example:-

1	2	3	4
Off	On	Off	On

The above is the normal default DIP Switch settings for a FCC3.

Turn Power Off to PCC3

Set DIP Switches as follows:-

1	2	3	4
Off	Off	Off	On

Turn Power On for 15 seconds & then back Off again.

Reset DIP Switches back to the original setting. They should be as follows.

1	2	3	4
Off	On	Off	On

Turn Power on to FCC3.

The POSTEC has now been reset & ready to accept the Site Configuration from the on site System. Eg On Q / Breeze.